



# Power generator **FH 3001 R**

Nr art. 36754

## Characteristic

- Voltage stabilization  $\pm 2\%$
- Low level of THD  $\leq 6\%$
- Shortcut starting current 300 %
- Alternator insulation class H
- Alternator protection IP 23

## Technical parameters

<b>Frequency</b>	<b>50 Hz</b>
<b>Voltage</b>	<b>230 V</b>
<b>Maximum power</b>	<b>2,7 kW</b>
<b>Nominal power</b>	<b>2,5 kW</b>
<b>Prime current</b>	<b>10,9 A</b>
Engine	Honda
Model	GX 200
Capacity	196 cm <sup>3</sup>
Cooling	Air
Cylinder	1
Stroke	4
Oil volume	0,6 L
Starting system	Manual
Fuel	Petrol
Fuel tank	3,1 L
Consumption (load 50/100%)	1,4 L / h
Noise level Lwa	96 dB(A)
Weight	37 kg
Length	580 mm
Width	395 mm
Height	405 mm

## Standard equipment

- AVR
- 2 sockets 230 V 16 A
- Overload protection
- Oil level sensor

## Optional and service equipment

- Exhaust hose Nr art. 15876
- Exhaust adapter Nr art. 10117
- Hourmeter Nr art. 23300
- Service kit  
(air filter, spark plug, engine oil) Nr art. 16581

## Norms and Directives

- **2000/14/WE**  
Noise Directive 2005/88/WE
- **2006/42/WE**  
Machinery Directive
- **2014/35/UE**  
Low Voltage Directive
- **2014/30/UE**  
EC Directive



**ETOP**  
creat să reziste

Republica Moldova, MD-2023  
mun. Chişinău, str. Uzinelor 90  
+ /373/ 67 707 707  
office@etop.md  
www.etop.md