



# Power generator **F 9000 R**

Nr art. 37075

## Characteristic

- Cyfrowa regulacja napięcia  $\pm 1,5\%$  na każdej fazie
- Low level of THD  $< 6\%$
- Shortcut starting current 300 %
- Alternator insulation class H
- Alternator protection IP 23

## Technical parameters

<b>Frequency</b>	<b>50 Hz</b>
<b>Voltage</b>	<b>400 / 230 V</b>
<b>Power 3~ max / nom.</b>	<b>8,3 kVA / 7,5 kVA (cos <math>\phi</math> 0,8)</b>
<b>Prime current 3~</b>	<b>10,9 A</b>
<b>Power 1~ max / nom.</b>	<b>5,0 kW / 4,5 kW</b>
<b>Prime current 1~</b>	<b>19,6 A</b>

Engine	Rato
Model	R 420
Capacity	420 cm <sup>3</sup>
Cooling	Air
Cylinder	1
Stroke	4
Oil volume	1,1 L
Starting system	Manual
Fuel	Petrol
Fuel tank	6,5 L
Consumption (load 75%)	2,9 L / h
Noise level Lwa	99 dB(A)

Weight	75 kg
Length	790 mm
Width	580 mm
Height	505 mm

## Standard equipment

- AVR
- Socket 400 V 16 A
- Socket 230 V 16 A
- Overload protection
- Oil level sensor

## Optional and service equipment

- Hourmeter Nr art. 23300
- Transportation set Nr art. 34994
- Service kit  
(air filter, spark plug, engine oil) Nr art. 35111

## Norms and Directives

- **2006/42/WE**  
Machinery Directive
- **2014/35/UE**  
Low Voltage Directive
- **2014/30/UE**  
EC Directive



**ETOP**  
creat să reziste

Republica Moldova, MD-2023  
mun. Chișinău, str. Uzinelor 90  
+ /373/ 67 707 707  
office@etop.md  
www.etop.md