



# Power generator

## F 9540

Nr art. 35604

### Characteristic

- Voltage stabilization  $\pm 5 - 10 \%$
- Low level of THD  $\leq 4 \%$
- Shortcut starting current 300 %
- Alternator insulation class H
- Alternator protection IP 54

### Technical parameters

<b>Frequency</b>	<b>50 Hz</b>
<b>Voltage</b>	<b>400 / 230 V</b>
<b>Power 3~ max / nom.</b>	<b>8,3 kVA / 7,5 kVA (cos <math>\phi</math> 0,8)</b>
<b>Prime current 3~</b>	<b>10,9 A</b>
<b>Power 1~ max / nom.</b>	<b>3,3 kW / 3,0 kW</b>
<b>Prime current 1~</b>	<b>13,0 A</b>

Engine	Rato
Model	R420
Capacity	420 cm <sup>3</sup>
Cooling	Air
Cylinder	1
Stroke	4
Oil volume	1,1 L
Starting system	Manual
Fuel	Petrol
Fuel tank	6,5 L
Consumption (load 75%)	2,9 L / h
Noise level Lwa	99 dB(A)

Weight	96 kg
Length	745 mm
Width	530 mm
Height	495 mm

### Standard equipment

- Socket 230 V 16 A IP 67
- Socket 230 V 16 A 3P IP 67
- Socket 400 V 16 A 5P IP 67
- Overload protection
- Oil level sensor
- Hourmeter

### Optional and service equipment

- Exhaust hose Nr art. 15876
- Exhaust adapter Nr art. 110118
- Transportation set (raçzki) Nr art. 34994
- Service kit (air filter, spark plug, engine oil) Nr art. 35111

### Norms and Directives

- **2006/42/WE**  
Machinery Directive
- **2014/35/UE**  
Low Voltage Directive
- **2014/30/UE**  
EC Directive



**ETOP**  
creat să reziste

Republica Moldova, MD-2023  
mun. Chişinău, str. Uzinelor 90  
+ /373/ 67 707 707  
office@etop.md  
www.etop.md