



# Power generator

## F 9540 TRA

Nr art. 35659

### Characteristic

- Digital voltage regulation  $\pm 2\%$  on three phases
- Low level of THD  $\leq 4\%$
- Shortcut starting current  $> 350\%$
- Alternator insulation class H
- Alternator protection IP 54
- Full single phase power output socket 32 Amps
- Autonomy (at 75 % load) 16,7 h
- Lowered noise level from 97 to 96 dB(A)
- Frame diameter 38 mm

### Technical parameters

<b>Frequency</b>	<b>50 Hz</b>
<b>Voltage</b>	<b>400 / 230 V</b>
<b>Power 3~ max / nom.</b>	<b>8,3 kVA / 7,5 kVA (cos <math>\phi</math> 0,8)</b>
<b>Prime current 3~</b>	<b>10,9 A</b>
<b>Power 1~ max / nom.</b>	<b>5,0 kW / 4,5 kW</b>
<b>Prime current 1~</b>	<b>19,6 A</b>

Engine	Rato
Model	R420
Capacity	420 cm <sup>3</sup>
Cooling	Air
Cylinder	1
Stroke	4
Oil volume	1,1 L
Starting system	Manual
Fuel	Petrol
Fuel tank	45 L
Consumption (load 75%)	2,9 L / h
Noise level Lwa	99 dB(A)

Weight	123 kg
Length	790 mm
Width	580 mm
Height	765 mm

### Standard equipment

- AVR
- Socket 400 V 16 A
- Socket 230 V 32 A
- Socket 230 V 16 A
- Overload protection
- Oil level sensor
- Silencer with exhaust adapter
- Hourmeter
- Battery

### Optional and service equipment

- Exhaust hose
  - Transportation set
  - Service kit (air filter, spark plug, engine oil)
  - ATS panel
- Nr art. 15876  
Nr art. 34995  
Nr art. 35447  
Nr art. 30312

### Norms and Directives

- **2006/42/WE**  
Machinery Directive
- **2014/35/UE**  
Low Voltage Directive
- **2014/30/UE**



**ETOP**  
creat să reziste

Republica Moldova, MD-2023  
mun. Chişinău, str. Uzinelor 90  
+ /373/ 67 707 707  
office@etop.md  
www.etop.md