



# Power generator

## FH 7001 TE

Nr art. 37006

### Characteristic

- Voltage stabilization  $\pm 5 - 10 \%$
- Low level of THD  $\leq 6 \%$
- Shortcut starting current 300 %
- Alternator insulation class H
- Alternator protection IP 23
- Full single phase power output socket 32 Amps
- Autonomy (at 75 % load) 16,7 h
- Lowered noise level from 97 to 96 dB(A)
- Frame diameter 38 mm

### Technical parameters

<b>Frequency</b>	<b>50 Hz</b>
<b>Voltage</b>	<b>230 V</b>
<b>Maximum power</b>	<b>6,2 kW</b>
<b>Nominal power</b>	<b>5,6 kW</b>
<b>Prime current</b>	<b>24,3 A</b>
Engine	Honda
Model	GX 390
Capacity	389 cm <sup>3</sup>
Cooling	Air
Cylinder	1
Stroke	4
Oil volume	1,1 L
Starting system	Manual + electric
Fuel	Petrol
Fuel tank	45 L
Consumption (load 50/100%)	2,7 L / h
Noise level Lwa	96 dB(A)
Weight	94 kg
Length	790 mm
Width	580 mm
Height	650 mm

### Standard equipment

- Socket 230 V 16 A
- Socket 230 V 32 A
- Overload protection
- Oil level sensor
- Silencer with exhaust adapter
- Battery

### Optional and service equipment

- Exhaust hose
  - Hourmeter
  - Transportation set
  - Service kit (air filter, spark plug, engine oil)
- Nr art. 15876  
Nr art. 23300  
Nr art. 34995  
Nr art. 23294

### Norms and Directives

- **2000/14/WE**  
Noise Directive 2005/88/WE
- **2006/42/WE**  
Machinery Directive
- **2014/35/UE**  
Low Voltage Directive
- **2014/30/UE**  
EMC Directive



**ETOP**  
creat să reziste

Republica Moldova, MD-2023  
mun. Chişinău, str. Uzinelor 90  
+ /373/ 67 707 707  
office@etop.md  
www.etop.md