



Power generator

F 3001

Nr art. 36115

Characteristic

- Regulația napięcia $\pm 5\%$
- Low level of THD $\leq 6\%$
- Shortcut starting current 250 %
- Alternator insulation class H
- Alternator protection IP 23

Technical parameters

Frequency	50 Hz
Voltage	230 V
Maximum power	3,0 kW
Nominal power	2,7 kW
Prime current	11,7 A
Engine	Rato
Model	R 210
Capacity	212 cm ³
Cooling	Air
Cylinder	1
Stroke	4
Oil volume	0,55 L
Starting system	Manual
Fuel	Petrol
Fuel tank	3,6 L
Consumption (load 50/100%)	1,4 L / h
Noise level Lwa	96 dB(A)
Weight	38 kg
Length	580 mm
Width	395 mm
Height	405 mm

Standard equipment

- 2 sockets 230 V 16 A
- Overload protection
- Oil level sensor

Optional and service equipment

- Hourmeter Nr art. 23300
- Service kit
(air filter, spark plug, engine oil) Nr art. 23295

Norms and Directives

- **2000/14/WE**
Noise Directive 2005/88/WE
- **2006/42/WE**
Machinery Directive
- **2014/35/UE**
Low Voltage Directive
- **2014/30/UE**
EC Directive



ETOP
creat să reziste

Republica Moldova, MD-2023
mun. Chișinău, str. Uzinelor 90
+ /373/ 67 707 707
office@etop.md
www.etop.md